- 1. 下載http://zwave.myehome.my/update/PouChen/old/2.13.1/sysupgrade_fw.bin
- 2. 連線到這台主機的系統設定畫面(http://<主機的IP>/)

Auth	norizat	tion R	equi	ired
Auu				

Please enter your username and password.

Username	root	
Password		
Login 🙆 Reset		

Powered by Avadesign / UltraHub Corsican Pine 2.13.0

- 3. 帳號root, 密碼1234.
- 4. 登入後, 點擊上方選單"System"-->"Backup / Flash Firmware".
- 5. 在這個頁面, 下半部的區塊是"Flash new firmware image", 請維持"Keep Settings"這個項目為勾選狀態.

Flash	operations				
Actions	ons Configuration				
Backup Click "Gene with squash	/ Restore rate archive" to dowr fs images).	lload a tar archive of the current config	uration files. To reset the firmware to its initial state, click "Perform reset" (only possible		
	Download backup:	Generate archive			
	Reset to defaults:	Perform reset			
o restore co	onfiguration files, you	can upload a previously generated bac	ckup archive here.		
	Restore backup:	選擇檔案 未選擇任何檔案	Upload archive		
-lash ne	ew firmware in	nage			
Jpload a sy compatible f	supgrade-compatible firmware image).	image here to replace the running firm	ware. Check "Keep settings" to retain the current configuration (requires an OpenWrt		
	Keep settings:				
	Image:	選擇檔案 未選擇任何檔案	Flash image		
Powered by	Avadosian / Ultra-Hu	h Corsican Bine 2 13 0			

- 6. 在"Image"這個項目點擊後會有對話窗要求選擇要上傳的firmware.
- 7. 選擇好後, 點擊"Flash image..."按鈕開始上傳.
- 8. 上傳完成後會跳轉頁面.

Flash Firmware - Verify

The flash image was uploaded. Below is the checksum and file size listed, compare them with the original file to ensure data integrity. Click "Proceed" below to start the flash procedure.

- Checksum: 999dca436d0e2058af0bf9728531de61
- Size: 11.13 MB (15.81 MB available)
- Configuration files will be kept.



9. 接著請確認這個頁面中的"Checksum"是否跟前面圖中一致, "Size"是否一致, 以及"Configuration file will be kept"這個訊息有 沒有顯示

10. 如果都正確的話, 就點擊"Preceed"開始firmware更新

System - Flashing...

The system is flashing now. DO NOT POWER OFF THE DEVICE! Wait a few minutes before you try to reconnect. It might be necessary to renew the address of your computer to reach the device again, depending on your settings.

Loading Waiting for changes to be applied...

11. 接著等待更新完成(約需5~10分鐘).